

## Electrical Signaling

Electrical protective signaling systems are configurations of components used to produce alarm signals indicative of fire, smoke, sprinkler waterflow or other emergency and to produce supervisory signals indicative of conditions needing attention with respect to protection equipment or watch service. System configurations are classified according to where and how the signals are received. The categories are commonly designated as local, municipal, remote station, proprietary, emergency voice/alarm communication, emergency communication, and central station. Auxiliary systems are either local or proprietary systems interconnected with a municipal system.

This category presents the major system component categories and the integrated system configurations. The selection of components to form a hybrid system should be made only by those skilled in system design. Also, the suitability of any system application should be judged on the basis of the hazard(s) being protected.

## Alarm Signal Initiating Devices

Alarm signals are initiated either automatically or manually. Automatic detectors respond to changes in characteristic phenomena associated with fire or other emergency conditions.

## Fire Detection, Smoke-Actuated

FM Approved smoke actuated devices respond to airborne particulate products of combustion.

The photoelectric principle is based on the change in current which accompanies a change in light intensity on a photoelectric cell as a result of smoke entering the detector.

The beam type version has the light source and photoelectric cell separated in the protected area.

The ionization type detector ionizes the air in special chambers within the detector.

Particles entering the exposed chamber decrease the normal ionization current.

Air-sampling detectors have ambient air drawn from the protected area into a chamber containing the sensing element.

Air duct smoke detectors are for the primary purpose of controlling blowers and dampers of air conditioning and ventilating systems to prevent distribution of smoke and gaseous products;

they should not be used as a substitute for open area detection.

Unless otherwise indicated in the listing, the permissible air velocity range for duct type detectors is 250 to 1500 ft/min (75 to 455 m/min) and up to 300 ft/min (90 m/min) for open area detectors.

A "smoke switch" is fail-safe in that loss of power to the device causes the same switching operation as when smoke is detected.

Average coverage should not exceed 900 ft<sup>2</sup> (84 m<sup>2</sup>) per detector. Reduced coverage is recommended beneath high ceilings and for high air flow areas such as computer rooms.

These devices are suitable for use in ambients of 32°-100°F (0°-38°C) unless otherwise indicated in the listing. Installation, testing, and maintenance by trained personnel are recommended.

## Fire Detectors-Smoke

### AS2011-00

#### PR456304

AS2011-00 addressable photoelectric smoke detector. To be used with compatible Approved fire alarm control panels Avenger – Oasis 2 Loop, 4 Loop or Avenger – Oasis 1 Loop, 2 Loop models only. Up to 127 devices are permitted on each panel's signaling line loop. Uses models AS7001-00 and AS7002-00 detector bases. Operating voltage range of 17 to 41V dc, with the standby current at 450 µA and alarm current at 540 µA. Air velocity range 0-4000 fpm. Suitable for indoor use only (unheated, but not refrigerated areas) with temperatures from 14°F to 122°F (-10° to 50°C). Avenger – Oasis 2 Loop, 4 Loop or Avenger – Oasis 1 Loop, 2 Loop Fire Alarm Control Panels listings under Local Protective Signaling)

<b>Company Name:</b>	Avenger Systems, LLC
<b>Company Address:</b>	11586 Zagarolo Lane, Las Vegas, Nevada 89141, USA
<b>Company Website:</b>	<a href="http://www.avengersystems.com">http://www.avengersystems.com</a>
<b>New/Updated Product Listing:</b>	Yes
<b>Listing Country:</b>	United States of America
<b>Certification Type:</b>	FM Approved